



T8 PRE-WIRED BALLAST

WE HAVE TURN-KEY RETROFITTING ALL WRAPPED UP!



TCP pre-wires and individually wraps the ballast, lampholders, and disconnect to save you time!

Sockets

High quality sockets includes lamp locking rotor and phosphor bronze alloy contacts for long life.



- Snap-in mount
- Fits a standard 9.6x25.5 mm hole
- PC Housing/PBT Rotor
- Shunted for IS use



All Components UL Certified

Disconnects

Upgrades the fixture to meet 2008 NEC requirements for luminaire disconnects; allows the fixture to be safely disconnected from the power supply before servicing.

- Orange Polycarbonate
- 18 Ga Solid Wire
- 600V
- 13.66" Long
- 105 C Temperature Rating
- UL94 V-2 Flammability Rating



RETROBALHARNWD1

GENERAL CHARACTERISTICS

Application	1 F32T8 120 to 277v 1.18BF
Ballast Type	Electronic – High Efficiency Multivolt Instant Start
Starting Method	Instant Start
Lamp Wiring	Parallel
Line Voltage Regulation (+/-)	10%
Ambient Temp . (Max)	105°F 41°C
Case Temp (Max)	167°F 75°C
Ballast Factor	High (1.18)
Sound Rating	A
Supply Current Frequency	50 Hz/60 Hz

DIMENSIONS

Case Dimensions	
Length (L)	9.5 in
Width (W)	1.3 in
Height (H)	1.0 in
Lead Lengths	
White/Black	25 in
Red/Blue	31 in
Weight	1.1 lbs.
Exit Type	Side
Remote Mounting Distance to lamp	18 ft.
Remote Mounting Wire Gauge	18 AWG

RETROBALHARNWD2 and RETROBALHARNWD4

GENERAL CHARACTERISTICS

Application	2 to 4 F32T8 120 to 277v 1.18BF
Ballast Type	Electronic – High Efficiency Multivolt Instant Start
Starting Method	Instant Start
Lamp Wiring	Parallel
Line Voltage Regulation (+/-)	10%
Ambient Temp . (Max)	105°F 41°C
Case Temp (Max)	167°F 75°C
Ballast Factor	High (1.18)
Sound Rating	A
Supply Current Frequency	50 Hz/60 Hz

DIMENSIONS

Case Dimensions	
Length (L)	9.5 in
Width (W)	1.3 in
Height (H)	1.0 in
Lead Lengths	
White/Black	25 in
Red/Blue	31 in
Weight	1.1 lbs.
Exit Type	Side
Remote Mounting Distance to lamp	18 ft.
Remote Mounting Wire Gauge	18 AWG